


The vLocML2+ Receiver

The vLocML2+ Receiver comes with passive modes of Power and Radio, a range of preloaded active frequencies from 50Hz to 200kHz, Sonde Mode, SD (Signal Direction) mode and Electronic Marker modes. The vLocML2+ has an internal memory to store over 1000 records of data.


The vLocML2+ can be used in three configurations suited to a particular function. The Line/Marker mode for all the functions for general pipe, cable and sonde locating and where all markers attached to lines are shown with depth. The Dedicated Line Location mode where all the functions for general pipe, cable and sonde locating are active and the dedicated Marker Mode for just marker locating.

The vLocML2+ Receivers accessory socket can enhance the locating experience with accessories such as the A-frame Fault Locator to pinpoint faults and cable cuts. The Remote Antenna to act as a stethoscope to positively identify a cable when in a tray.


- Large full-color screen
- Auto depth readout of buried markers
- Rechargeable and alkaline batteries
- Left/Right locate arrows
- Bluetooth and GPS options
- Compass line direction indicator



Utility locate mode



Dedicated marker



Combined mode



Backed by Vivax-Metrotech's superior dealer network, customer service and service.

1 (800) 446-3392

Specifications:

User interface	Speaker and color dot matrix LCD
Weight	4.16lbs (2.1kg)
Dimensions	10.3" x 4.8" x 25" (262mm x 122mm x 639mm)
Frequency range	Active modes: 16Hz to 200kHz, Passive modes Radio, power and EMS Markers
Measurements	Marker depth, cable and sonde depth, current, signal strength, cable direction (compass)
Range	Depends on signal strength but typically more than 7m
Accuracy	+/- 5%
Power supply	6 off AA alkaline or dedicated Li-ion rechargeable pack
Accessories	Fault find A-Frame, Remote Antenna
Environmental	Weather resistant IP54

Compatible Transmitters:

Model/Output Power	Weight	Environmental	Frequency Range	Max Output Current	Power Source
Loc-1Tx - 1 Watt	3.7lbs (1.65kg)	IP54	512Hz to 83kHz	150mA	4 x alkaline "D" cells
Loc-5STx - 5 Watt	4.6lbs (2.09kg)	IP54	512Hz to 83kHz, Fault-find and Signal Direction (SD)	300mA	8 x alkaline "D" cells, optional Li-ion rechargeable battery kit
Loc-10Tx - 10 Watt	11lbs (5kg)	IP54	98Hz to 200kHz, Fault-find, Signal Direction (SD) and SIS (Signal Select)	1A	12 x alkaline "D" cells Optional Ni-MH rechargeable kit, optional 12-16V external DC power cord.

Your local Vivax-Metrotech dealer is:

Vivax-Metrotech AUS

Unit 1, 176 South Creek Rd
Cromer NSW 2099
Tel: +61 (0)2 9972 9244
Fax: +61 (0)2 9972 9433
Email: sales@vxmtaus.com

Vivax-Metrotech Corporation

3251 Olcott Street, Santa Clara, CA 95054, USA
T/Free: 800-446-3392
Tel: 408-734-1400
www.vivax-metrotech.com



Disclaimer: Product and accessory specification and availability information is subject to change without prior notice. V1.1 (Sept 2016)